

SMOKE DETECTOR

This sensor detects the presence of smoke. It works with all SensorHawk base units (*SensorHawk-2*, *SensorHawk-8* and *SensorHawk8/20*) as well as the *SecurityHawk* base units. SNMP traps and sensor polling available (*MIB file supplied*).

Specifications

- No calibration required.
- LED indicator visually indicates alarm status.
- **Available Lengths:** 1.5m (5 feet)
- Receive an email message if an alert condition is triggered, or start up another piece of equipment with optional *Sensor Controlled Relay*.
- **Disconnect Alarm:** Relay alert if sensor becomes interrupted or disconnected.
- **Mounting Options:** Ceiling mount recommended, mounting hardware supplied.
- **Sensor Type:** Open (Smoke Not Detected) / Closed (Smoke Detected) Contact Switch



PART# SH-SK-00

